

## SATCOM COMPONENT

# **M&C Cable Assembly** for BUC



### TYPICAL SPECIFICATIONS

#### **Electrical Specifications**

J1 (10pin) RS232, Ethernet, External mute

RS232 J2 (3pin)

J3 (4pin) Ethernet

J4 (3pin) External mute

#### **Mechanical Specifications**

J1 (10pin) MS3116A 12S-10S, female

J2 (3pin) DS-09S, female

J3 (4pin) RJ-45, male J4 (3pin) open wires

Length between J1 and J4

> 1m (depending on request)

Weight < 500g (for 3m cable)

Color Black


#### **Environmental Specifications**

Operating temperature -50 to 100 ℃

#### **Applications**

- · Used to monitor and control the BUC via RS232 or Ethernet communication, and the external mute
- · Can be used at the outdoors because J1 connector is water-proof

# **HOW TO ORDER M&C CABLE ASSY**




Version 1.0 M&C Cable Assy




## SATCOM COMPONENT

## **CABLING CONFIGURATION**

## Configuration of BUC + Power Supply + Cable Assembly



# Pin map of M&C cable connector



Description	J1 Pin No.	J2 Pin No.	J3 Pin No.	J4 Pin No.
RS-232 Tx	Α	2	-	-
RS-232 Rx	В	3	-	-
Ethernet Rx-	С	-	6	-
-	D	-	-	D
Ext. Mute GND	E	-	-	E*
Ext. Mute (High)	F	-	-	F*
Ethernet Tx+	G	-	1	-
RS-232 GND	Н	5	-	-
Ethernet Rx+	J	-	3	-
Ethernet Tx-	K	-	2	-

<sup>\*</sup> When J4-E and J4-F connected, external mute is inactivited . When J4-E and J4-F disconnected, external mute is activied.

Version 1.0 M&C Cable Assy